

# R7

## POWERED BY INTELLECT. DRIVEN BY PERFORMANCE.



Extreme Long Range Radar & Laser Detector



-  Radar Arrow Alert Using Dual Antenna
-  360° Laser Protection
-  Large Ultra-Bright OLED Display
-  Digital Signal Processor
-  GPS for red-light and speed cameras
-  Voice Alert
-  Advanced K/KA Filter
-  Mute Memory
-  Spectre Elite Undetectable

# NEW ZEALAND DEVELOPED SOFTWARE TUNED FOR OUR MARKET



## KEY FEATURES

- ✘ Uniden's highest performance detector with dual horns and directional arrows
- ✘ Advanced digital signal processing (DSP)
- ✘ Users can choose a variety of display and arrow colours
- ✘ Extreme sensitivity, highest ever from Uniden
- ✘ GPS with red light and speed camera alerts for NZ sites
- ✘ BSM filter to filter out false signals from Crash Avoidance Systems
- ✘ Quiet Ride – User set speed for auto mute
- ✘ Updatable via USB connection to PC
- ✘ Uniden offers a large, bright, full color OLED display
- ✘ Multi-function display includes voltage, compass, altimeter, time of day and current speed
- ✘ Segmented K Band to eliminate speed signs and other false signal areas
- ✘ K false filter
- ✘ Ka false filter
- ✘ Segmented Ka band for unparalleled performance
- ✘ Detects MultaRadar (MRCD/MRCT)

## INCLUDED ACCESSORIES

- ✘ Single and dual suction cup windshield mounting brackets
- ✘ 12V cigarette power adapter with USB port and mute button
- ✘ Micro USB cable (for firmware updates)
- ✘ Neoprene pouch
- ✘ Carrying case

## Uniden® R7 NZ SPECIFICATIONS

### OPERATING BANDS

X-band: 10.525 GHz ± 25 MHz (Off for NZ)

K-band: 23.900 GHz to 24.250GHz (NZ Speed Camera Specification)

Ka-Super Wideband: 33.400 GHz to 36.110GHz

Laser: 904nm, 33MHz bandwidth

### K-BAND SEGMENT FREQUENCIES

K1 – 23.900 – 24.110GHz

K2 – 24.110 – 24.250GHz

### SUPERWIDE KA BAND SEGMENT FREQUENCIES

Ka1 – 33.392 – 33.704GHz

Ka2 – 33.704 – 33.896GHz

Ka3 – 33.886 – 34.198GHz

Ka4 – 34.186 – 34.592GHz

Ka5 – 34.592 – 34.808GHz

Ka6 – 34.806 – 35.166GHz

Ka7 – 35.143 – 35.383GHz

Ka8 – 35.378 – 35.618GHz

Ka9 – 35.595 – 35.835GHz

Ka10 – 35.830 – 35.998GHz

### DISPLAY TYPE

OLED display

Bar Graph, Frequency Display, Current Speed  
3 levels of fixed brightness or auto dimming  
including full Dark

